



# Digital Signature Validation Library

*Version 1.0*

*Digital Signature Competencies Center*

*Information Technology Industry Development Agency*

## Error code

Code	Message	Description
4040	Invalid digital signature format	Couldn't parse digital signature because it is not a valid CAdES format.
4041	Couldn't parse digital signature	Couldn't parse or validate CAdES attributes
4042	Digital signature integrity failed	Digital signature verification has failed using signer's public key.
4043	[.NET Message]	Digital signature integrity has failed
4044	Verification failed because time of signature is invalid	Verification has failed because signature doesn't contain signature time
4045	[.NET Message]	Digital signature is invalid because the hash of signer certificate doesn't match with the hash the user has signed on.
4046	Signature is invalid due to incorrect SigningCertificateV2 attribute value.	Digital signature is invalid because it couldn't parse Signing Certificate V2 attribute from the signature.
4048		Message Digest signed attribute is not found.
4049	Couldn't parse digital signature.	Couldn't parse digital signature. Check the inner exception.
4062	Encapsulated data in the signature is not allowed	Encapsulated data in the signature is not allowed
4065	CAdES – T signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
4066	CAdES – C signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
4067	CAdES – X Type 1 is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
4068	CAdES – X Type 2 is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
4069	CAdES – X Long is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
4070	CAdES – XL Type 1 is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
4071	CAdES – XL Type 2 is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
4072	CMS Signature is not allowed	CMS Signature is not allowed. Only valid CAdES-BES format is allowed.
4073	CMS Signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.

<b>4074</b>	CMS Signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
<b>4075</b>	CMS Signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
<b>4076</b>	CMS Signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
<b>4077</b>	CMS Signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
<b>4078</b>	CMS Signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
<b>4079</b>	CMS Signature is not allowed	Digital signature format is not supported. Only valid CAdES-BES format is allowed.
<b>4101</b>	[.NET Message]	Failed to Generate OCSP Request.
<b>4102</b>	[.NET Message]	Couldn't send OCSP request because connection has failed.
<b>4103</b>	[.NET Message]	Failed to connect to OCSP another error has occurred.
<b>4104</b>	Couldn't parse OCSP response	OCSP Server returned an invalid OCSP Response
<b>4105</b>	Invalid OCSP Response Signature	Invalid OCSP Response Signature
<b>4106</b>	Invalid OCSP Certificate	Invalid OCSP Certificate
<b>4107</b>	OCSP Connection type is not supported	OCSP Connection type is not supported
<b>4108</b>	[.NET Message]	Exception was thrown while checking revocation status of the certificate using OCSP
<b>4151</b>	Cannot verify a self-signed certificate	Self-signed certificate cannot be validated. Certificate should be signed from Egypt Root CA.
<b>4152</b>	The Certificate is not yet valid at (Signature Time)	The Certificate is not yet valid at (Date Time)
<b>4153</b>	Couldn't check the revocation status of the certificate	Failed to check revocation status using both OCSP and CRL. Check errors returned from GetVerificationErrorStack() function for more detailed errors (see <a href="#">CertificateVerificationException</a> ).
<b>4154</b>	Couldn't verify certificate because certificate chain doesn't reach Egypt Root CA certificate.	Certificate is not trusted.
<b>4155</b>	Couldn't build certificate chain because one or more of the issuer certificates are missing	Couldn't build certificate chain because one or more of the issuer certificates are missing and need to be installed on the machine.
<b>4156</b>	The certificate is revoked on (Signature Time)	Certificate is revoked (Checked by OCSP)
<b>4157</b>	The certificate is revoked on (Signature Time)	Certificate is revoked (Checked by CRL)
<b>4158</b>	Couldn't build certificate chain	Couldn't build certificate chain. Check the inner exception.
<b>4159</b>	The Certificate is expired at (Date Time)	The Certificate is expired at (Date Time)

<b>4164</b>	Certificate cannot be null	
<b>4201</b>	Couldn't check revocation status of the certificate because there is no CRL distribution points in the certificate	Certificate doesn't contain neither OCSP Server URL nor CRL URL to check the revocation status
<b>4202</b>	[CRL URL] Couldn't verify CRL signature	CRL's signature is not verified by the issuer certificate.
<b>4203</b>	[CRL URL] CRL is expired	Couldn't check revocation status using this CRL because it is expired
<b>4205</b>	Couldn't check the revocation status of the certificate	Exception was thrown during revocation status check of the certificate using CRL. Check the inner exception.
<b>4210</b>	There is no CRL distribution points in the certificate	Couldn't check revocation status of the certificate because CRL Distribution Points extension is not found
<b>4213</b>	Certificate verification failed because time to check the certificate is ahead of the current time	Certificate verification failed because time to check the certificate is in the future.
<b>4214</b>	Couldn't check the revocation status of the certificate	Couldn't check revocation status because the CRL as well as the Issuing CA are expired.
<b>4402</b>	CRL URL + .NET Message	Failed to download CRL using HTTP protocol.
<b>4403</b>	CRL URL + .NET Message	Failed to download CRL from LDAP
<b>3008</b>	Error in verifying License	
<b>3013</b>	Error in activating License	
<b>3014</b>	Error in checking License	
<b>3015</b>	Error in checking License online	
<b>3016</b>	Error in checking License online	
<b>3017</b>	Failed to save License Data	
<b>3018</b>	Unable to load License Data	
<b>3019</b>	Unable to load License Data	
<b>3020</b>	Failed to save License Data, No Write Permission	
<b>3022</b>	Error in activating license online	
<b>3023</b>	Error in Loading License Details	
<b>3400</b>	Error occurred while getting license, Invalid or missing parameters	
<b>3480</b>	Error occurred while getting license, this machine is blacklisted	
<b>3481</b>	Error occurred while getting license, Database connection failure	
<b>3482</b>	Error occurred while getting license, Invalid product key	
<b>3483</b>	Error occurred while getting license, License maximum count exceeded	
<b>3484</b>	Error occurred while getting license, License expired	

<b>3485</b>	Error occurred while getting license, Invalid HW key	
<b>3486</b>	Error occurred while getting license, This product key is blacklisted	
<b>3487</b>	Error occurred while getting license, Unsupported Operating System	
<b>3488</b>	Unable to get Machine ID	
<b>3489</b>	Unable to get Machine ID	
<b>3502</b>	Invalid License Key	
<b>3503</b>	License isn't valid yet.	
<b>3504</b>	License Expired, Please Re-new it.	
<b>3505</b>	This License is not intended for this machine	
<b>3506</b>	This License is not intended for this application	
<b>3507</b>	License is Missing	
<b>3510</b>	Your License Data is modified, Please re-configure the license	
<b>3511</b>	Your License configuration is corrupted, Please restart the application	
<b>3512</b>	System time isn't correct, Please adjust the time	